



Quick Installation Guide

## **EtherFast 10/100M Switch**

Model No.: SP616EB

<http://www.micronet.info>

## **Introduction**

Micronet SP616EB 10/100M Switch provides powerful, high-performance Ethernet switch, with all 16 ports capable of 10M and 100M auto-negotiation operation. With its intelligent addressing engine, it provides users with a wire-speed filtering and forwarding of the traffic. All ports support auto-uplink detection, so users don't have to worry about the cable type. Each port will automatically communicate for best speed and to run in half- or full-duplex mode. Store-and-forward switching function prevents damaged packets and network errors from being passed on into the network.

## **Package Contents**


Before installing the device, please verify the following items are in the package:

- EtherFast 10/100M Switch
- Quick Installation Guide
- Power cord

## Features

- Compliant with IEEE802.3 10Base-T, IEEE802.3u 100Base-TX and IEEE802.3x flow control
- Supports speed (10/100Mbps) and duplex mode(Half/Full) and auto-detection
- Supports MDI/MDI-X auto crossover
- Supports full and half duplex operation on all ports
- Supports back-pressure (Half/Full) and flow control (IEEE 802.3x)
- Supports extensive LED indicators for network diagnostics
- Wire-speed packet filtering and forwarding rate
- Store-and-forward architecture filters fragment & CRC error packets
- 10" and 19" rack-mountable

## Physical Description



SP616EB front view

Please refer to the following table for LED definition.

LED	Status	Operation
POWER	On	Power is on.
	Off	Power is off.
LNK/ACT	On/Green	Connection established.
	Blink/Green	Transmitting or receiving data.
	Off	No link.

## Installation

Installation is easy-- simply connect the cables and the power cord. The system is ready, and you can use all the features.

Connect each station to the switch by twisted-pair cable. Plug one of the RJ-45 connectors into a RJ-45 port of the switch, and plug the other RJ-45 connector into the station's network adapter. Power on the switch and then the system is ready.

All ports could be used to connect with another switch. As all the ports support auto-uplink (MDI / MDI-X) function, user can choose to use a straight cable or a crossover cable to make a switch-to-switch connection.

For cable selection, refer to the following table :

Network Speed	Connector	Cable Type	Max. Length
10BaseT	RJ-45	Cat. 3, 4, 5 UTP/STP	100 m
100BaseTX	RJ-45	Cat. 5 UTP/STP	100 m

**Note:** *To prevent costly equipment damage and downtime, please consider installing a surge suppression device or a UPS (Un-interrupted Power Supply).*

## Specifications

<b>Standard</b>	IEEE802.3, IEEE802.3u, IEEE802.3x, compliant
<b>Interface</b>	16 * 10/100M RJ-45 ports
<b>Cable Connections</b>	10BASE-T: Cat. 3, 4, 5 UTP/STP 100BASE-TX: Cat. 5 UTP/STP
<b>MAC address</b>	8K
<b>Buffer Memory</b>	160K Byte for the whole system
<b>NWay Protocol</b>	Network speed:10Mbps and 100Mbps Duplex mode: Full and Half
<b>Uplink</b>	Auto Uplink (Auto MDI / MDI-X)
<b>Filtering/Forwarding Rate</b>	10Mbps: 14,880pps/14,880pps 100Mbps: 148,800pps/148,800pps
<b>Emission</b>	FCC Class A, CE
<b>Operating Temperature</b>	0° - 40° C (32° - 104° F)
<b>Operating Humidity</b>	10% - 90% (Non-condensing)
<b>Dimension (mm)</b>	267 × 161 × 44
<b>Weight (kg)</b>	1.2
<b>Power Supply</b>	100 ~ 240V AC, 50/60Hz Full range internal power supply

## **CE Mark Warning**

This equipment complies with the requirements relating to electromagnetic compatibility, the essential protection requirement of Council Directive 89/336/EEC on the approximation of the laws of the Member States relating to electromagnetic compatibility.

Company has an on-going policy of upgrading its products and it may be possible that information in this document is not up-to-date. Please check with your local distributors for the latest information. No part of this document can be copied or reproduced in any form without written consent from the company.

Trademarks:

All trade names and trademarks are the properties of their respective companies.

Copyright © 2005, All Rights Reserved



P/N:

## Free Manuals Download Website

<http://myh66.com>

<http://usermanuals.us>

<http://www.somanuals.com>

<http://www.4manuals.cc>

<http://www.manual-lib.com>

<http://www.404manual.com>

<http://www.luxmanual.com>

<http://aubethermostatmanual.com>

Golf course search by state

<http://golfingnear.com>

Email search by domain

<http://emailbydomain.com>

Auto manuals search

<http://auto.somanuals.com>

TV manuals search

<http://tv.somanuals.com>