

# SPECIFICATIONS



## UMA™ 35T II Mixer Amplifier

### SPECIFICATIONS

#### Output Power:

35 watts

#### Frequency Response:

##### Power Amplifier:

Direct:  $\pm 0.5$  dB, 20 Hz to 20 kHz  
XFMR:  $\pm 0.5$  dB, 50 Hz to 20 kHz

##### Preamplifier:

$\pm 1.5$  dB, 50 Hz to 20 kHz

#### Distortion:

##### Power Amplifier:

0.02% (1 kHz)

##### Preamplifier:

< 0.1% with nominal gain settings

#### S/N Ratio:

Master Volume Min:  
95 dB below rated power

Master Volume Max:  
80 dB below rated power

High-Z Inputs:  
75 dB below rated power

Low-Z Inputs:  
65 dB below rated power

#### Power Bandwidth:

Direct: 20 Hz to 20 kHz < 0.5% THD

XFMR: 50 Hz to 20 kHz < 0.5% THD

#### Output Regulation:

Direct: < 0.5 dB

XFMR: < 1.0 dB

#### Outputs:

Direct: 4 ohms  
XFMR: 8 ohms, 600 ohms, 25 V, and  
70 V (balanced)

Ch. 3 Output, Loop Out, AUX Out:  
1 V @ 100 ohms

#### Inputs:

##### Channel 1:

Low-Z 500  $\mu$ V @ 1.8 K ohms (XLR or  
screw terminals)

High-Z 50 mV @ 9.5 K ohms  
(screw terminals)

##### Channel 2:

Low-Z 500  $\mu$ V @ 1.8 K ohms  
(screw terminals)

High-Z 50 mV @ 9.5 K ohms (RCA or  
screw terminals)

##### Channel 3:

High-Z 50 mV @ 9.5 K ohms (RCA)

Page: 100 mV (600 ohm transformer  
balanced screw terminals)

Loop In: 1 volt @ 3.6 K ohms

#### Tone Controls:

Bass:  $\pm 10$  dB @ 100 Hz

Treble:  $\pm 10$  dB @ 10 kHz

Contour: +6 dB @ 100 Hz and 10 kHz

#### Controls:

Channel 1 Volume Control

Channel 2 Volume Control

Channel 3 Volume Control

Page 1 Volume Control (rear panel  
screwdriver adjust)

Page Mute Threshold Control (rear  
panel screwdriver adjust)

Channel 1 Mute Threshold Control  
(rear panel screwdriver adjust)

Bass Control

Treble Control

Master Volume Control

Contour Switch

Link Switch

Power Switch

#### Indicators:

Power Indicator (Red LED)

Activity Indicator (Green LED)

SPS™ Active Indicator (Yellow LED)

Mute 1 and Mute 2 Indicators (Yellow  
LEDs)

#### Muting:

Mute 1: Page input overrides  
Channels 1 through 3 with  
adjustable threshold

Mute 2: Channel 1 overrides Channels  
2 and 3 with adjustable  
threshold

#### Power Requirements:

120 V AC, 60 Hz

#### Other Features:

Remote Volume Control via screw  
terminals

Mute 1 and Mute 2 switch closure via  
screw terminals

15 V DC phantom power on Low-Z  
inputs

#### FEATURES

- Two mic/line inputs with screw terminals on each; one with XLR and one with dual RCA phono jacks
- One line level input with dual RCA phono jacks
- One dedicated 600 ohm transformer balanced paging input with screw

**PEAVEY**  
ARCHITECTURAL ACOUSTICS®

- terminals and rear panel screwdriver adjust level control
- Two mute lines, providing internal signal override or external switch closure, with adjustable thresholds and indicators
- Provisions for external master volume control
- Bass, Treble, and Contour EQ controls
- Loop Out/Loop In patch point with RCA phono connectors and link switch
- Channel 3 output (RCA phono), which gives a non-mutable output of Channel 3
- AUX output for tape recorders, etc.
- Signal activity indicator
- Power indicator
- SPS™ (Speaker Protection System) circuitry with indicator
- 4 ohm, 8 ohm, 25 V and 70 V transformer-isolated outputs
- 600 ohm balanced line level output
- AC convenience outlet
- Powder coated steel chassis
- Optional rack-mounting kits available

## DESCRIPTION

The UMA™ 35T II is a versatile mixer/amplifier designed for numerous sound reinforcement applications. The flexible input configurations make it an excel-

lent choice for paging and/or back/foreground music systems. The UMA™ Series mixer/amplifiers are ready for any job, utilizing an isolated transformer with multiple output configurations.

## ARCHITECTURAL & ENGINEERING SPECIFICATIONS

The mixer amplifier shall have two microphone/line inputs, one line input, and one dedicated page input. Channel 1 shall have screw terminals and an XLR connector for the Low-Z input; screw terminals for the Hi Z input. Channel 2 shall have screw terminals for the Low-Z input; screw terminals and RCA phono connectors for the High-Z inputs. Channel 3 shall have RCA phono connectors. Channels 1 and 2 shall have 15 volt phantom power for the Low-Z inputs. The page input shall be transformer balanced (600 ohms) and shall have screw terminals for the input connection.

The master section shall include one master volume level control, two EQ controls providing 10 dB boost or cut at 100 Hz and 10 kHz, and a "Contour" switch providing 6 dB of boost at 100 Hz and 10 kHz.

The unit shall have two levels of automatic muting. Mute 1 shall give

precedence to the page input, and it shall override Channels 1 through 3, with a threshold control on the page input. Mute 2 shall give precedence to Channel 1, and it shall override Channels 2 and 3, with a threshold control on Channel 1. The two mute lines shall have screw terminals for external mute control.

The unit shall have a Channel 3 output that provides an RCA phono, non-mutable output of Channel 3. Provision for an external master volume control shall be made via screw terminals.

The unit shall be packaged in a rugged metal chassis 17" wide by 3-1/2" high by 15-5/8" deep. The unit shall operate from standard 120 volts AC, 60 Hz power. The internal power amplifier shall be capable of delivering 35 watts into 4 ohms and 8 ohms, as well as providing 25 volt and 70 volt balanced line outputs. The unit shall be capable of delivering rated power from 20 Hz to 20 kHz  $\pm 1.5$  dB into 4 ohms at its direct output at 0.5% or less distortion with hum and noise at least 80 dB below rated output from line level inputs. The unit shall be called the Peavey Architectural Acoustics Division model UMA™ 35T II.

## LIMITED WARRANTY

Peavey Electronics Corporation warrants to the original purchaser of this new Architectural Acoustics product that it is free from defects in material and workmanship. If within one (1) year from date of purchase a properly installed product proves to be defective and Peavey is notified, Peavey will repair or replace it at no charge. (Note: Batteries and patch cords not covered.) "Original purchaser" means the customer for whom the product is originally installed.

Damage resulting from improper installation, interconnection of a unit or system of another manufacturer, accident or unreasonable use, neglect or any other cause not arising from defects in material and workmanship is not covered by this warranty. The warranty is valid only as to products purchased and installed in the United States and Canada.

**THIS LIMITED WARRANTY IS IN LIEU OF ANY AND ALL WARRANTIES, EXPRESSED OR IMPLIED, INCLUDING THE IMPLIED WARRANTIES OF MERCHANTABILITY AND FITNESS FOR A PARTICULAR USE. UNDER NO CIRCUMSTANCES WILL PEAVEY BE LIABLE FOR ANY LOST PROFITS, LOST SAVINGS, INCIDENTAL DAMAGES OR CONSEQUENTIAL DAMAGES ARISING OUT OF THE USE OR INABILITY TO USE THE PRODUCT, EVEN IF PEAVEY HAS BEEN ADVISED OF THE POSSIBILITY OF SUCH DAMAGE. THIS LIMITED WARRANTY IS THE ONLY EXPRESSED WARRANTY ON THIS PRODUCT, AND NO OTHER STATEMENT, REPRESENTATION, WARRANTY, OR AGREEMENT BY ANY PERSON SHALL BE VALID OR BINDING UPON PEAVEY.**

Peavey's liability to the original purchaser for damages for any cause whatsoever and regardless of the form of action is limited to the actual damages up to the greater of Five Hundred Dollars (\$500) or an amount equal to the purchase price of the product that caused the damage or that is the subject of or is directly related to the cause of action. This limitation of liability will not apply to claims for personal injury or damage to real property or tangible personal property allegedly caused by Peavey's negligence. For information on service under this warranty, call a Peavey customer service representative at (601) 483-5376.



Features and specifications subject to change without notice.

A Division of Peavey Electronics Corporation

711 A Street / Meridian, MS 39301 / U.S.A. / (601) 483-5376 / Fax 486-1154

#80302293



©1994

Printed in U.S.A. 12/94

## Free Manuals Download Website

<http://myh66.com>

<http://usermanuals.us>

<http://www.somanuals.com>

<http://www.4manuals.cc>

<http://www.manual-lib.com>

<http://www.404manual.com>

<http://www.luxmanual.com>

<http://aubethermostatmanual.com>

Golf course search by state

<http://golfingnear.com>

Email search by domain

<http://emailbydomain.com>

Auto manuals search

<http://auto.somanuals.com>

TV manuals search

<http://tv.somanuals.com>