



# Perreaux

Model: SM5

Date of Manufacture: 1994

Product Type: Stereo Preamplifier

## Specifications:

<b>Frequency Response</b> .....	10Hz-65kHz, +0.0dB -0.4dB
<b>Input Sensitivity</b>	
All inputs .....	200mV <sub>rms</sub>
<b>Input Impedance</b>	
All inputs .....	20k $\Omega$
<b>Input Overload</b>	
All inputs .....	10V <sub>rms</sub>
<b>Rated Output</b> .....	1.5V <sub>rms</sub> into 10k $\Omega$ or higher
<b>Maximum Output</b> .....	22V <sub>rms</sub> into 10k $\Omega$ or higher
<b>Main Output</b>	
Source Impedance .....	600 $\Omega$
<b>Tape Output Level</b> .....	220mV
<b>Minimum Recommended Load</b> .....	10k $\Omega$
<b>Distortion (THD and IMD)</b>	
All inputs (at rated output into 10k $\Omega$ or higher) .....	< 0.001% 20Hz-20kHz
<b>Noise (inputs loaded, A weighted)</b> .....	-103dB
Typically .....	-106dB
<b>Channel Separation</b>	
Unweighted .....	80dB 20Hz-20kHz
<b>Dimensions</b>	
Width .....	483mm (19.0")
Height .....	66mm (2.6")
Depth .....	312mm (12.3")
<b>Weight</b> .....	7.0kg (15.4lbs)

- Schematic diagram
- Product manual

---

info@perreaux.com

www.perreaux.com

## Free Manuals Download Website

<http://myh66.com>

<http://usermanuals.us>

<http://www.somanuals.com>

<http://www.4manuals.cc>

<http://www.manual-lib.com>

<http://www.404manual.com>

<http://www.luxmanual.com>

<http://aubethermostatmanual.com>

Golf course search by state

<http://golfingnear.com>

Email search by domain

<http://emailbydomain.com>

Auto manuals search

<http://auto.somanuals.com>

TV manuals search

<http://tv.somanuals.com>