


7" WALL WASH ELEMENTS

**E7P383LWW Lensed Wall Wash (Includes Lamp Module)**

Add Cone Color and Flange style (see p. 732)

Module/Lamp: P7: 90W PAR38/3
PN7: 150W PAR38/3

Dimensions: OD: 8 1/4" (210mm) Aperture: 6 3/4" (172mm)

**E7QT4WW Wide Spread Lensed Wall Wash**

Add Cone Color and Flange style (see p. 732)

Module/Lamp: P7 with MQT4 Module: Q100T4/MC
PN7 with MQT4 Module: Q150T4/MC

Dimensions: OD: 8 1/4" (210mm) Aperture: 6 3/4" (172mm)



7" SHOWER/LENSED ELEMENTS

**E7LUNA Wet Location Blown Veined Glass**

Module/Lamp: P7 with M42T Module: 26/32/42W Triple Compact Fluorescent
PN7 with M42T Module: 26/32/42W Triple Compact Fluorescent
P7 with M32TLUTRON Module: 32W Triple Compact Fluorescent
PN7 with M32TLUTRON Module: 32W Triple Compact Fluorescent
P7 with M42T277 Module: 26/32/42W Triple Compact Fluorescent
An Emergency version is available for compact fluorescent units.
P7 with M120 Module: 150W A21, 100BT15, 100W MB19
PN& with M120 Module: 150W A21, 100BT15, 90W BT19, 100W MB19

Dimensions: OD: 8 3/4" (222mm)

**E7SR Wet Location Regressed Lens**

Add Cone Color and Flange style (see p. 732)


Module/Lamp: P7 with M42T Module: 26/32/42W Triple Compact Fluorescent
PN7 with M42T Module: 26/32/42W Triple Compact Fluorescent
P7 with M32TLUTRON Module: 32W Triple Compact Fluorescent
PN7 with M32TLUTRON Module: 32W Triple Compact Fluorescent
P7 with M42T277 Module: 26/32/42W Triple Compact Fluorescent
An Emergency version is available for compact fluorescent units.
P7 with M120 Module: 100W A21, 75W TB15, 75W MB19
PN7 with M120 Module: 100W A21, 75W TB15, 75W MB19

Dimensions: OD: 8 1/4" (210mm) Aperture: 6 3/4" (172mm)

**E7QT4 Wet Location 50° Cutoff Reflector**

Add Cone Color and Flange style (see p. 732)

Module/Lamp: P7 with MQT Module: Q150T4/MC
PN7 with MQT Module: Q150T4/MC
OD: 8 1/4" (210mm) Aperture: 6 3/4" (172mm)



ELEMENT OPTIONS

Cone Finishes:

C = Clear Specular Alzak
H = Haze Clear Semi-Specular Alzak
G = Champagne Gold Specular Alzak
B = Specular Black Alzak
WMH = Warm Haze Semi-specular Alzak with a hint of gold to add visual warmth
W = Gloss White Paint
MW = Matte White
K = Cognac = Warm copper color, specular Alzak
KH = Cognac Haze = Cognac, semi-specular Alzak
GP = Graphite = Gunmetal grey, specular Alzak
GPH = Graphite Haze = Graphite, semi-specular Alzak

Baffle Options

BB = Black Baffle
WB = White Baffle

Flanges

Blank = Matte white die-cast flange ring, removable for field painting
RAW = Die cast trim ring, mill finish
SF = Self Flange (flange color matches reflector cone)
SFWF = Self Flange painted Matte White

Example:

E7T
Cone Finish | Flange Type and Finish

Example:

E7A21
Baffle Finish | Flange Type and Finish (self flange not available)

Free Manuals Download Website

<http://myh66.com>

<http://usermanuals.us>

<http://www.somanuals.com>

<http://www.4manuals.cc>

<http://www.manual-lib.com>

<http://www.404manual.com>

<http://www.luxmanual.com>

<http://aubethermostatmanual.com>

Golf course search by state

<http://golfingnear.com>

Email search by domain

<http://emailbydomain.com>

Auto manuals search

<http://auto.somanuals.com>

TV manuals search

<http://tv.somanuals.com>