

JVC

LT-Z26EX6 LT-Z32EX6

WIDE LCD PANEL TV INSTRUCTIONS

JVC




LT-Z26EX6

DynaPiX HD
Powered by D.L.S.


HDMI
HIGH-DEFINITION MULTIMEDIA INTERFACE




1




2



3




4



JVC

Expanding the world of beautiful images



Contents

First things first!

- Warning 3

Getting started

- Names of all the parts 5
- Basic connections 7
- Initial settings 9
- Editing channels 11
 - Registering channels
- Connecting external devices 13

Let's try it out

- Enjoying your new TV! 15
 - TV / Teletext / Video / etc.
- Watching TV 17
- Viewing teletext 19
- Watching videos / DVDs 21

Try the advanced features

- Useful functions 23
 - Take a snapshot
 - View and search in multi-picture mode
 - "Sleep Timer" / "Channel Guard"

Just the way you like it

- Customising your TV 27
- Advanced picture adjustment 29
 - Reduce noise / Watch a more natural picture
 - Set the aspect ratio, etc.

When you have trouble

- Troubleshooting 31
- Technical information 35
- "CH/CC" List 37
- Specifications 38

Warning

Please follow all the guidelines below

ENGLISH

Follow this manual regarding setup!

- Connect only to a 110-240V, 50/60Hz AC outlet.

Do not allow the TV to fall!

- Do not rest your elbows on, or allow children to hang from the TV. There is a risk that the TV will fall and cause injuries.

When attaching the TV to the wall, use the optional JVC wall mounting unit!

- Consult a qualified technician.
- See the included manual on mounting procedures.
- JVC assumes no responsibility for damage due to improper mounting.

Never place anything on the TV!

- Placing liquids, naked flames, cloths, paper, etc. on the TV may cause a fire.




Make enough room for inserting and removing the power plug!

Place the TV as close to the outlet as possible!

- The main power supply for this TV is controlled by inserting or removing the power plug.

Never cut or damage the power cord!

- If the AC plug is not the right shape, or the power cord is not long enough, use an appropriate plug adapter or extension cable. (Consult your retailer.)



Never try to repair the TV yourself!

- ➔ If the problem cannot be solved in "Troubleshooting" (P. 31), unplug the power cord and contact your retailer.

If the TV is damaged or behaving strangely, stop using it at once!

- ➔ Unplug the power cord and contact your retailer.

Never expose to rain or moisture!

- To prevent fire or electric shock, never allow liquids to enter the unit.



Never insert objects into the cabinet openings!

- It may cause a fatal electric shock. Take care when children are near.




Never listen to headphones at high volume!

- It may damage your hearing.

Unplug the power cord when going out!

- The power buttons on the remote control and the TV unit cannot completely turn off the TV. (Make appropriate arrangements for bedridden people.)



Never dismantle the rear panel!

- It may cause an electric shock.

Never obstruct the ventilation holes!

- It may cause overheating or a fire.

Handle LCD panel with care!

- Use a soft, dry cloth when cleaning.

Hold the TV so as not to scratch the screen!

- Do not touch the screen when carrying the TV.

Do not carry the TV on your own!

- In order to prevent accidents, ensure that the TV is carried by two or more people.



■ For more details on installation, usage and safety ➔ Consult your retailer

ENGLISH

IMPORTANT!

PREPARE


USE

SETTINGS


TROUBLE?

Names of all the parts

ENGLISH




Remove the terminal cover



- If the cover cannot be closed due to the cables being in the way
 ➔ Do not force the cover to close (leave it open).
- Connecting terminals on the back of the TV ➔ Connecting External devices (P. 13)

Check accessories



ENGLISH


IMPORTANT!

PREPARE

USE

SETTINGS

TROUBLE?



■ When watching TV / Video
 Change the aspect ratio (P. 17)
 Turn on "Cinema Surround" (P. 17)

ZOOM CINEMA

Take a snapshot of the screen (P. 23)
 View in multi-picture mode (P. 23)

■ Insert the batteries
 Use two "AA/R06" dry cell batteries.
 Insert the batteries from the ⊖ end, making sure the ⊕ and ⊖ polarities are correct.

■ When viewing teletext (P. 19)
 Hold the current page
 Bookmark pages
 Reveal hidden pages
 Enlarge the text

MODE
 TOP MENU


Switch briefly between teletext and TV
 To index page

Basic connections

Please read the user manuals of each device carefully before setup.
It is necessary to connect an aerial to watch TV.


■ Connect with other devices → "Connecting external devices" (P. 13)

Connect the aerial



- After all the connections have been made, insert the plug into an AC outlet.

Connect a VCR / DVD recorder



- After all the connections have been made, insert the plug into an AC outlet.
- If both composite and S-VIDEO cables are connected, S-VIDEO will be enable.

Care when setting

■ Power requirements


- Connect the power cord only to a 110-240V, 50/60Hz AC outlet.

■ When attaching the TV to the wall, use the optional JVC wall mounting unit


- Consult a qualified technician.
- See the included manual on mounting procedures.
- JVC assumes no responsibility for damage due to improper mounting.
- 200mm × 200mm mount which conforms to VESA standards.

■ Installation requirements

- To avoid overheating, ensure the unit has ample room.



Tidying the cables



- To remove the cable cover, refer to back of the cover.

Initial settings

Set the menu language, installation location and automatically register the TV channels. These channels can be edited later in "Editing channels" (P. 11).

1 Begin

- Shown only when powering on for the first time.
- The power on the unit can also be used.

2 Select a language

3 Select the teletext language group

- For the teletext language group → "Language group for teletext" (P. 35)
- If the characters are unreadable. → "Language group for teletext" (P. 35)

4 Automatically register channels

5 Check what was registered

PR	ID	CH	CHCC
01		CH 21	
02		CH 22	
03		CH 23	
04		CH 24	
05		CH 25	
06		CC 02	
07		CC 03	
08		CC 04	
09		CC 05	

- Edit channels → 4 in "Editing channels" (P. 11)


6 Confirm

- To the previous screen →
- Exit →
- If the "JVC" logo does not appear or if you wish to make changes later → "Language", "Teletext language" and "Auto Program" (P. 28)

Editing channels

Edit the channels registered with "Auto Program" in "Initial settings" (P. 9).

ENGLISH



When coming from "Initial settings" (P. 9), skip to 4.

- 1 Display the menu bar
MENU
- 2 Select "Set Up"
Set Up
- 3 Select "Edit / Manual"
Edit/Manual
- 4 Select a row
CH 21
- 5 Edit
ID
- 6 Finish

- To the previous screen
BACK
- Exit MENU

Move a channel's position
MOVE

Edit a channel name
ID

Insert a channel
INSERT

Delete a channel
DELETE

Register a new channel
MANUAL

1 Begin 2 Select a destination 3 Finish

1 Begin 2 Enter a channel name

1 Begin 2 Select a "CH / CC" 3 Enter a number

● "CH/CC" List → (P. 37)

1 Delete

1 Begin 2 Beginning channel search From high frequencies ZOOM or From low frequencies CINEMA

● Auto-search begins, and the nearest frequency is imported.
➔ Repeat the previous steps until the desired channel is displayed

■ Adjust

- Channel fine tuning →
- If the picture or sound is unnatural → select a system

ENGLISH

IMPORTANT!

PREPARE

USE

SETTINGS


TROUBLE?

Connecting external devices


You can connect many different devices to the rear panel of the TV.
Please read the user manuals of each device before setting up.
(Connecting cables are not supplied with this TV.)

VCR / DVD / other devices

ENGLISH



⇒ : signal direction



VIDEO-1 Watching videos

Output ↑	Input ↓
	· Composite signal / · Component signal · S-VIDEO · Sound L / R

- Use Component signal
→ "Switch between video and component signal" (P. 22)
- Use S-VIDEO
→ "Using S-VIDEO" (P. 22)

VIDEO-2 Watching videos

Output ↑	Input ↓
	· Composite signal / · S-VIDEO · Sound L / R

- Use S-VIDEO
→ "Using S-VIDEO" (P. 22)

VIDEO-3 Watching DVDs

Output ↑	Input ↓
	· Composite signal / · Component signal · Sound L / R

- Use Component signal
→ "Switch between video and component signal" (P. 22)

HDMI Connecting HDMI devices

Output ↑	Input ↓
	· HDMI signal (P. 36)

- "HDMI Setting" → (P. 28)

OUT

Video and sound signal of a TV channel you are viewing outputs from this terminal

Output ↓
· Composite signal / · S-VIDEO · Sound L / R

- "Using OUT terminal". → (P. 22)

- Connect a "DVI" device to "HDMI" → (P. 36)

ENGLISH

IMPORTANT!

PREPARE

USE

SETTINGS



TROUBLE?

Enjoying your new TV!

Watching TV

PAGE
17

- View channel information
- Change the aspect ratio
- Enjoy "Cinema Surround"
- Register your favourite channels



Watching videos / DVDs

PAGE
21


- Watch high quality video (S-VIDEO)
- Switch between video and component signal
- PC position adjustment

TV/VIDEO

Viewing teletext

PAGE
19


- Enlarge the text
- To the index page
- Hold the current page
- Switch briefly between teletext and TV
- Bookmark your favourite pages
- Reveal hidden pages



Personal preferences

PAGE
27

- Adjust the picture
- Adjust the sound
- Advanced settings (sleep-timer / channel guard, etc.)
- Basic settings (channel settings, etc.)



Watching TV

ENGLISH

1 **Power on**
 The blue power lamp on the TV lights
 ● Press again to turn the screen off and put the TV into standby mode.

2 **Select a channel**
 E.g. 1 : 0 → 1
 15 : 1 → 5
 ■ Move up or down a channel
 CHANNEL up
 CHANNEL down

■ Switch between mono / stereo / bilingual broadcasting
 → "Stereo / I-IT" (P. 28)

Note
 ● To completely turn off the TV, unplug the AC plug.

■ Mute

■ Volume

Basic operations using the side buttons

1 Power on

2 Change the channel

■ Volume

Channel information

DISPLAY

PR List
 ● Channels registered in "Initial settings" will appear here.

Channel information
 (No indication)

■ Select a page → select

■ Select and view a channel → select
 view

Change the aspect ratio

ZOOM

ZOOM
 Auto
 Regular
 Panoramic
 16:9 Zoom
 16:9 Zoom
 Full

1 select
 2 set

16:9 Zoom

Move the picture with ▲ or ▼ while this bar is displayed

- When set to "Auto", the aspect ratio will turn to the ratio obtained from the information the TV received. Without receiving aspect information, it will be the setting in "Auto" of "Zoom" (P. 30)
- Not available in 1080i (1125i) / 720p (750p) signals.
- In PC mode, "Regular" and "Full" can be selected.

Enjoy ambient sound

CINEMA SURROUND

CINEMA SURROUND
 Cinema Surround High

High : For stereo sound
 Low : For stereo sound (when the sound distorts in "High" mode)
 Mono : For mono sound (emulates a stereo-like sound)
 Off : Turns off "Cinema Surround"

Always return to the channel you want to view

RETURN PLUS

■ Registered as return channel
 While the channel is displayed
 RETURN+ Hold down for 3 seconds

Return Plus Programmed!

■ Cancel
 While the channel is displayed
 RETURN+ Hold down for 3 seconds

Return Plus Canceled!

■ Recall the return channel → RETURN+

Return to the last channel you were viewing

RETURN

RETURN+

Current channel ↔ Last channel

ENGLISH

IMPORTANT!

PREPARE

USE

SETTINGS

TROUBLE?

Viewing teletext

This TV can display TV broadcasts and teletext on the same channel in two windows.

ENGLISH

1 When watching TV

2 Enter a teletext page

1 2 3
4 5 6
7 8 9
0

■ Move up or down a page

CHANNEL up
down

■ View sub-pages

to sub-page

TV TEXT
TEXT TEXT
TEXT TEXT

Bookmark your favourite page

LIST MODE

- Display your favourites list MODE
- Select a coloured button to save your page to (RED) (GREEN) (YELLOW) (BLUE)
- Enter the number of the page to save
- Save

■ Recall your favourite page → Press the coloured button as in step 2

Hold the current page
HOLD
■ Release → Press "INFO" again

Reveal hidden pages
REVEAL
Display hidden information (answers to quizzes, etc.)

Enlarge the text
SIZE
Double the size of the displayed text

To the index page
INDEX
Returns to page "100" or a previously designated page

Switch briefly from teletext to TV
CANCEL
Leave the current page open, while you switch to watch TV
● Useful when running a page search.

ENGLISH

IMPORTANT!

PREPARE


USE




SETTINGS

TROUBLE?





Watching videos / DVDs

ENGLISH




- Select the video source**
 →  → 
 - 0 01
 - 1 Video-1
 - 2 Video-2
 - 3 Video-3
 - 4 HDMI
 - 5 PC
- Operate the connected device and play a video**





Operate JVC VCRs and other devices

- DVD players**

- VCRs and DVD recorders**

- Turn on the device**

- Select a channel (VCR mode)**

 - ◀ Rewind / Playback / Fast-forward
 - ⏸ Stop / Pause
 - ▶ Record / Display DVD top menu
 - ⏪ Select a chapter (DVD mode)

● Some models of JVC devices cannot be operated with this remote control.

Switch between video and component signal



- Display the menu bar**

- Select "Set Up"**

- Select "Video-1 Setting" or "Video-3 Setting"**

- Change settings**

 - Video** : For normal video signal
 - Component** : For component video signal


Using S-VIDEO






- If both composite and S-VIDEO cables are connected, S-VIDEO will be enable.

Using OUT terminal

- Component and PC signals does not output from this terminal.
- When you are viewing video signal, no signal will output through the S-VIDEO terminal.
- HDMI inputs does not output from this terminal.

PC position adjustment



- Display the menu bar**

- Select "Set Up"**

- Select "PC Position"**

 - Shown only when "PC" is selected.
- Adjust and set**

 - Reset position → 

ENGLISH

IMPORTANT!

PREPARE

USE

SETTINGS

TROUBLE?

Useful functions

ENGLISH

Select the number of screens

1 select
2 set

Selecting "1" returns to normal viewing mode
● Not available in PC mode.

■ Watch in dual-picture mode
E.g. You can watch TV and video at the same time.
(For wide aspect ratio signals)

Watch in multi-picture mode

MULTI-PICTURE

- Switch between the sound sources
→ (Main)
- Change the channel
→ (Main)
→ (Sub)

■ Select a channel in 12-screen mode
All registered channels are displayed as still images.

1 select a channel
2 watch

Only the selected frame has a moving picture.


- Move up or down a page
- Not available for HDMI input.

Take snapshots of the screen

FREEZE

■ Cancel
→ Press "OK" again, or change the channel

- Not available when the SUB-PICTURE is displayed, or when in PC mode.
- You cannot save or export the snapshot.



Set a time for the TV to turn itself off

SLEEP TIMER

- MENU
- 1 select "Features"
2 next
- 1 select "Sleep Timer"
2 next
- 1 select a time in minutes
2 set

- Cancel → Set the time to "0" in step 4
- Remaining time → You can confirm the remaining time at step 4, after repeating this process.

● After steps 1 and 2 above

- 3 select "Channel Guard"
- 4 1 enter an "ID No." (a secret number of your choice)
2 to the next column
3 set
- 5 select a channel to lock
- 6 Lock more channels
→ Repeat steps 5 and 6
- 7

- Release a channel → Press "OK" again in step 6
- View a locked channel → Use the numerical buttons to enter the channel number. When "ID No." appears, press "DISPLAY" and enter your "ID No." (If you forget your "ID No.", check it in step 4.)

Stop children from watching specific channels

CHANNEL GUARD

ENGLISH

IMPORTANT!

PREPARE

USE


SETTINGS


TROUBLE?


Useful functions (continued)


Register a channel to a button

FAVOURITE CHANNEL

1 While the channel is displayed
 Hold down for 3 seconds





2 Press the number to register it on






Disappears after a few seconds

Recall the favourite channel

1 



2 Press the number you registered







● Customisations (P. 28) to the picture of a favourite channel get saved as well.


Check your favourite channels



→ Press "MENU" and confirm that the channels you have registered have a  beside them

Delete a favourite channel

1 → "MENU" →  → "Features" → "Favourite Setting"



2 delete 

Displays a blue screen and mutes the sound when the signal is weak

BLUE BACK

→ "MENU" →  → "Features" → "Blue Back"






1 select

2 set

Off : Function is turned off

On : Displays a blue screen



When the signal is weak or absent

Displays a blue screen and mutes the sound

Set the power to turn off if no signal is received and no operation is performed

AUTO SHUTOFF

→ "MENU" →  → "Features" → "Auto Shutoff"






1 select

2 set

Off : Function is turned off

On : Set the power to turn off



When no signal is received and no operation is performed for about 15 minutes

The power turns off

Prevent sudden increase or decrease of sound when changing channels

AI VOLUME

→ "MENU" →  → "Set Up" → "AI Volume"

1 select


2 set

Off : Function is turned off

On : Set to prevent sudden increase or decrease of sound

Customising your TV

ENGLISH



1 Display the menu bar
 Press the MENU button.

2 Select a menu
 Press the **1** select button to choose a menu (Picture, Sound, Features, Set Up). Press the **2** next button to navigate between items.

3 Select an item
 Press the select button to enter a sub-menu.

4 Adjust / Configure
 Press the **1** adjust / select button to move a slider or select a preset. Press the **2** set button to confirm.

■ To the previous screen
 Press the BACK button.
■ Exit MENU
 Press the MENU button.
 ● The menu disappears after one minute of inactivity.

■ When adjusting with the sliding-bar
 Press the **1** adjust button to move the slider. Press the **2** set button to confirm.

■ When selecting from presets
 Press the **1** select button to choose a preset (e.g., Standard). Press the **2** set button to confirm. The item will change.

● Some items have a sub-menu.

Menu	Item	Adjustments / Configurations
Picture	Picture Mode	Picture mode (Bright / Standard / Soft)
	Back Light	Backlight brightness (Darker ⇄ Brighter)
	Contrast	Contrast (Lower ⇄ Higher)
	Bright	Brightness (Darker ⇄ Brighter)
	Sharp	Sharpness (Softer ⇄ Sharper)
	Colour	Colour (Lighter ⇄ Deeper)
	Tint	Tint (Reddish ⇄ Greenish) Only NTSC
	White Balance	Colour temperature (Warm / Mid / Cool)
	Features	Finer picture adjustments (P. 29)
	Sound	Stereo / I · II
Bass		Low tones (Weaker ⇄ Stronger)
Treble		High tones (Weaker ⇄ Stronger)
Balance		Speaker balance (Left Stronger ⇄ Right Stronger)
Cinema Surround		Ambience level (High / Low / Mono / Off)
Features	Tone Correction	Make the sound more clear (On / Off)
	Sleep Timer	Timer for turning off the TV (P. 24)
	Channel Guard	Stops children from watching specific channels (P. 24)
	Appearance	Format for displaying the channel number and menu screen. (Type A / Type B)
	Blue Back	Displays a blue screen and mute the sound when the signal is weak or absent (P. 26)
	Child Lock	Disables the front control buttons of the TV
	Auto Shutoff	Set the power to turn off if no signal is received and no operation is performed for about 15 minutes. (P. 26)
	Favourite Setting	Clear favourite channel settings (P. 25)
	Power Lamp	Lights power lamp (P. 5) while the TV is on (On / Off)
	Set Up	Auto Program
Edit / Manual		Change registered channels or add new ones (P. 11)
Language		Select a language for on-screen menus (P. 10, 2)
Video-1 Setting		For use with video players and other devices (P. 22)
Video-3 Setting		For use with video players and other devices (P. 22)
AI Volume		Prevent sudden increase or decrease of sound when changing channels (P. 26)
Teletext Language		Select a language for Teletext programmes (P. 10, 3)
HDMI Setting		HDMI : Size (1 / 2 / Auto) Audio (Digital / Analogue / Auto)
PC Position	PC position adjustment (P. 21)	

- Other settings · Change the aspect ratio → "ZOOM" (P. 17)
- Turn on "Cinema Surround" → "CINEMA SURROUND" (P. 17)

ENGLISH

IMPORTANT!

PREPARE

USE


SETTINGS

TROUBLE?

Advanced picture adjustment

By default, the TV automatically adjusts itself for the best picture.

ENGLISH



- 1 **Display the menu bar**
MENU
- 2 **Select "Picture"**
select next
- 3 **Select "Features"**
select next
- 4 **Select an item**
select next
E.g. "Super DigiPure"
- 5 **Change settings**
select
E.g. "Super DigiPure"
- 6 **Finish**
select

■ To the previous screen
BACK

■ Exit
MENU

● The menu disappears after one minute of inactivity.

ENGLISH

IMPORTANT!

PREPARE

USE

SETTINGS

TROUBLE?

Super DigiPure	For natural-looking outlines		<input type="checkbox"/> Off	<input type="checkbox"/> Min	<input type="checkbox"/> Max	<input type="checkbox"/> Auto	: Function is turned off : When the picture loses sharpness : When noise appears : Automatically adjusts
Pull Down	For smooth cinema film		<input type="checkbox"/> Off	<input type="checkbox"/> On	<input type="checkbox"/> Auto		: Function is turned off : Function is always on : Automatically adjusts
Colour Management	For natural-looking pictures		<input type="checkbox"/> Off	<input type="checkbox"/> On			: Function is turned off : Maintain a natural colour balance
Picture Management	Fix bright / dark pictures		<input type="checkbox"/> Off	<input type="checkbox"/> On			: Function is turned off : Make it easier to view bright / dark pictures
Smart Picture	Fix brightness of white areas		<input type="checkbox"/> Off	<input type="checkbox"/> On			: Function is turned off : Make it easier to view white areas ● Not available when "Picture Mode" is set to "Bright" (P. 28).
MPEG Noise Reduction	To reduce MPEG video noise		<input type="checkbox"/> Off	<input type="checkbox"/> On			: Function is turned off : When noise appears
Colour System	When there is no colour		<input type="checkbox"/> Main	<input type="checkbox"/> Sub			① Select the screen to change settings on : Main picture : Sub-picture in MULTI-PICTURE mode (P. 23) ② Select the colour system <input type="checkbox"/> PAL <input type="checkbox"/> SECAM <input type="checkbox"/> NTSC 3.58 <input type="checkbox"/> NTSC 4.43 <input type="checkbox"/> Auto ● For colour system in your country or region. ➔ "Colour system in your country or region" (P. 35)
Zoom	Change the aspect ratio		<input type="checkbox"/> Auto	<input type="checkbox"/> Regular	<input type="checkbox"/> 14:9 Zoom	<input type="checkbox"/> 16:9	Select a default aspect ratio for Auto in "Zoom" (P. 17) <input type="checkbox"/> 16:9 <input type="checkbox"/> 4:3 <input type="checkbox"/> 14:9

Troubleshooting

ENGLISH

Severe noise or snow



- Is the TV connected correctly to the aerial?
- Change the direction of the aerial.
- Is the aerial or its cable damaged?
 - ➔ Consult your retailer

Patterns, stripes or noise




- Is the aerial receiving interference from high-voltage power lines or wireless transmitters?
 - ➔ Consult your retailer
- Are connected devices too close to the TV?
 - ➔ Insert the minimum distance between the aerial and the cause of interference until no interference

Ghosting

(Doubling of images)




- Are you receiving interference from signals reflected off mountains or buildings?
 - ➔ Adjust the direction of your aerial, or change to a good-quality directional aerial



I can't turn it on!

- Is the power cord connected to the AC outlet correctly?



The remote control doesn't work!

- Are the batteries flat?
- Are you more than 7 meters away from the TV?
- Is the "MODE (VCR / TV / DVD)" set to "TV"?
- When viewing teletext, the TV menu bar does not appear.
- Depending on the stability of the signal, there may be a time lag when changing channels.

	Problem	Actions	page
Basics	Remote control stops working	● Unplug TV, several minutes later plug it in again.	-
	Front control buttons does not work	● Switch "Child Lock" to "Off".	28
Screen	Aspect ratio changes unintentionally	● Press "ZOOM" to return to your settings.	17
	PC screen alignment is off	● Adjust the "PC position".	21
Picture	Poor picture quality	● Unnatural colour >>> Adjust "Colour" and "Back Light". Check your "Colour System". If "Auto" is selected, select the specific colour system manually. Noise >>> Set to the following functions. Picture Mode : Standard Super DigiPure : Max Dull picture >>> Set to the following functions. Picture Mode : Bright Super DigiPure : Min	28 30 28 30 28 30
	Strange picture when using an external device	● If the top of the image is distorted, check the video signal quality itself. ● If movement appears unnatural when receiving a signal from a DVD player, etc. with 625p (progressive-scanning), change the output setting of the external device to 625i (interlace-scanning).	- -
	Blue screen appears on the screen	● Switch "Blue Back" to "Off".	26

ENGLISH

IMPORTANT!

PREPARE

USE

SETTINGS

TROUBLE?

Troubleshooting (continued)

ENGLISH

	Problem	Actions	page
Sound	Poor sound	<ul style="list-style-type: none"> ● Adjust the "Bass" and "Treble". ● If receiving a poor signal in "Stereo / I-II", switch to "Mono". ● Adjust the channel reception using "Manual". 	28 28 11
	Wrong screen size	<ul style="list-style-type: none"> ● Switch "Size" in "HDMI Setting" to "1" or "2". 	28
HDMI	No picture, no sound	<ul style="list-style-type: none"> ● Use the cable marked with HDMI logo. HDMI 	-
	No sound	<ul style="list-style-type: none"> ● Check if the device is compliant with HDMI. ● Switch "Audio" in "HDMI Setting" to "Digital" or "Auto" for HDMI devices, or "Analogue" or "Auto" for DVI devices. 	- 28
	Green and distorted screen	<ul style="list-style-type: none"> ● Wait a little for the signal to stabilize when switching the signal format for an "HDMI" device. 	-
	Some functions do not work	<ul style="list-style-type: none"> ● It is not a malfunction. Some functions (dark background) in the menu do not work depending on the situation. 	-
Functions	Some inputs cannot be selected in the sub-picture	<ul style="list-style-type: none"> ● "VIDEO-1 (Component signal)", "VIDEO-3 (Component signal)", "HDMI" inputs and PC mode cannot be selected in the sub-picture. 	-

	Problem	Actions	page
Screen	Black or white dots appear on the screen	<ul style="list-style-type: none"> ● LCD panels use fine dots ("pixels") to display images. While more than 99.99% of these pixels function properly, a very small number of pixels may not light, or may light all the time. Please understand that this is not a malfunction. 	-
OUT terminal	No picture, no sound	<ul style="list-style-type: none"> ● Some inputs does not output from OUT terminal 	22

ENGLISH

IMPORTANT!

PREPARE

USE

SETTINGS

TROUBLE?

Technical information

Language group for teletext

Group	Languages
Group-1	Turkish, Hungarian, English, German, French, Italian, Spanish, Portuguese, Greek, Swedish, Finnish
Group-2	Polish, Serbian, Croatian, Slovenian, Czech, Slovak, Rumanian, Hungarian, German, French, Italian, Swedish, Finnish
Group-3	Russian, Bulgarian, Lettish, Lithuanian, Estonian, Ukrainian, Serbian, Croatian, Slovenian, Czech, Slovak, English, German
Group-4	Arabic, Czech, Slovak, Hungarian, English, German, French, Italian, Spanish, Portuguese, Swedish, Finnish
Group-5	Farsi, Czech, Slovak, Hungarian, English, German, French, Italian, Spanish, Portuguese, Swedish, Finnish

- If the characters are unreadable. → Select different teletext language group.

Colour system in your country or region

Area	Country or Region	System
Asia, Middle East	Bahrain, Kuwait, Oman, Qatar, United Arab Emirates, Yemen, etc. Indonesia, Malaysia, Singapore, Thailand, India, etc.	PAL
	China, Vietnam, etc.	
	Hong Kong, etc.	SECAM
	Islamic Republic of Iran, Lebanon, Saudi Arabia, etc.	NTSC
Europe	Philippines, Taiwan, Myanmar, etc.	SECAM
	Russia, etc.	PAL
	Czech Republic, Poland, etc.	
	Germany, Holland, Belgium, etc.	
Oceania	UK, etc.	PAL
Africa	Australia, New Zealand, etc.	PAL
	Republic of South Africa, etc.	PAL
	Nigeria, etc.	SECAM
	Egypt, Morocco, etc.	SECAM

Sound system in your country or region

Area	Country or Region	System
Asia, Middle East	Bahrain, Kuwait, Oman, Qatar, United Arab Emirates, Yemen, etc. Indonesia, Malaysia, Singapore, Thailand, India, etc.	B/G
	China, Vietnam, etc.	D/K
	Hong Kong, etc.	I
	Islamic Republic of Iran, Lebanon, Saudi Arabia, etc.	B/G
Europe	Philippines, Taiwan, Myanmar, etc.	M
	Russia, etc.	D/K
	Czech Republic, Poland, etc.	
	Germany, Holland, Belgium, etc.	
Oceania	UK, etc.	I
Africa	Australia, New Zealand, etc.	B/G
	Republic of South Africa, etc.	I
	Nigeria, etc.	B/G
Egypt, Morocco, etc.		

Monoaural sound

Use this function when stereo sound or bilingual sound is hard to hear.

- Set "Stereo / I · II" to "MONO" → (P. 28)

PC Signals that can be displayed

Macintosh computers are not supported. (Macintosh is a registered trademark of Apple Computer, Inc.)

Resolution	640 x 480 (VGA)	1024 x 768 (XGA)
Vertical frequency (Hz)	60.0	60.0

- If the signal doesn't appear, check that the vertical frequency on the PC is set to "60Hz".

Connect "DVI" devices

Connect a "DVI" device to "HDMI" using "DVI-HDMI" conversion cable. Connect analogue sound output of the DVI device to L and R terminals in IN HDMI.

- Set "Audio" in "HDMI Setting" to "Analogue" or "Auto" → (P. 28)

"CH/CC" List

To use the INSERT function (P. 11), find the "CH/CC" number corresponding to the TV's Channel number from this table.

US: The US channel numbers are the channel numbers used in the United States, Philippines, etc.
 CCIR: The CCIR channel numbers are the channel numbers used in the Middle East, Southeast Asia, etc.
 OIRT: The OIRT channel numbers are the channel numbers used in Eastern Europe, Russia, Vietnam, etc.
 AUSTRALIA: The AUSTRALIA channel numbers are the channel numbers used in Australia, etc.

CH	Channel				AUSTRALIA	CC	Channel				AUSTRALIA
	US	CCIR	OIRT				US	CCIR	OIRT		
CH 02	US-02	E2	R1		AU-0	CC 01		S-1			
CH 03	US-03	E3			AU-1	CC 02		S-2			
CH 04	US-04	E4	R2		AU-2	CC 03		S-3			
CH 05	US-05	E5	R6		AU-6	CC 04		S-4			
CH 06	US-06	E6	R7		AU-7	CC 05		S-5			
CH 07	US-07	E7	R8		AU-8	CC 06		S-6			AU-5A
CH 08	US-08	E8	R9		AU-9	CC 07		S-7			
CH 09	US-09	E9				CC 08		S-8			
CH 10	US-10	E10	R10		AU-10	CC 09		S-9			
CH 11	US-11	E11	R11		AU-11	CC 10		S-10			
CH 12	US-12	E12	R12			CC 11		S-11			
CH 13	US-13					CC 12		S-12			
CH 14	US-14, W+29					CC 13		S-13			
CH 15	US-15, W+30					CC 14	A	S-14			
CH 16	US-16, W+31					CC 15	B	S-15			
CH 17	US-17, W+32					CC 16	C	S-16			
CH 18	US-18, W+33					CC 17	D	S-17			
CH 19	US-19, W+34					CC 18	E	S-18			
CH 20	US-20, W+35					CC 19	F	S-19			
CH 21	US-21, W+36	E21				CC 20	G	S-20			
CH 22	US-22, W+37	E22				CC 21	H	S-21			
CH 23	US-23, W+38	E23				CC 22	I	S-22			
CH 24	US-24, W+39	E24				CC 23	J	S-23			
CH 25	US-25, W+40	E25				CC 24	K	S-24			
CH 26	US-26, W+41	E26				CC 25	L	S-25			
CH 27	US-27, W+42	E27				CC 26	M	S-26			
CH 28	US-28, W+43	E28				CC 27	N	S-27			
CH 29	US-29, W+44	E29				CC 28	O	S-28			
CH 30	US-30, W+45	E30				CC 29	P	S-29			
CH 31	US-31, W+46	E31				CC 30	Q	S-30			
CH 32	US-32, W+47	E32				CC 31	R	S-31			
CH 33	US-33, W+48	E33				CC 32	S	S-32			
CH 34	US-34, W+49	E34				CC 33	T	S-33			
CH 35	US-35, W+50	E35				CC 34	U	S-34			
CH 36	US-36, W+51	E36				CC 35	V	S-35			
CH 37	US-37, W+52	E37				CC 36	W	S-36			
CH 38	US-38, W+53	E38				CC 37	W+1	S-37			
CH 39	US-39, W+54	E39				CC 38	W+2	S-38			
CH 40	US-40, W+55	E40				CC 39	W+3	S-39			
CH 41	US-41, W+56	E41				CC 40	W+4	S-40			
CH 42	US-42, W+57	E42				CC 41	W+5	S-41			
CH 43	US-43, W+58	E43				CC 42	W+6				
CH 44	US-44, W+59	E44				CC 43	W+7				
CH 45	US-45, W+60	E45				CC 44	W+8				
CH 46	US-46, W+61	E46				CC 45	W+9				
CH 47	US-47, W+62	E47				CC 46	W+10				
CH 48	US-48, W+63	E48				CC 47	W+11				
CH 49	US-49, W+64	E49				CC 48	W+12				
CH 50	US-50, W+65	E50				CC 49	W+13				
CH 51	US-51, W+66	E51				CC 50	W+14				
CH 52	US-52, W+67	E52				CC 51	W+15				
CH 53	US-53, W+68	E53				CC 52	W+16				
CH 54	US-54, W+69	E54				CC 53	W+17				
CH 55	US-55, W+70	E55				CC 54	W+18				
CH 56	US-56, W+71	E56				CC 55	W+19				
CH 57	US-57, W+72	E57				CC 56	W+20				
CH 58	US-58, W+73	E58				CC 57	W+21				
CH 59	US-59, W+74	E59				CC 58	W+22				
CH 60	US-60, W+75	E60				CC 59	W+23				
CH 61	US-61, W+76	E61				CC 60	W+24				
CH 62	US-62, W+77	E62				CC 61	W+25				
CH 63	US-63, W+78	E63				CC 62	W+26				
CH 64	US-64, W+79	E64				CC 63	W+27				
CH 65	US-65, W+80	E65				CC 64	W+28				
CH 66	US-66, W+81	E66				CC 75		X			
CH 67	US-67, W+82	E67				CC 76		Y			
CH 68	US-68, W+83	E68				CC 77		Z	R3		AU-3
CH 69	US-69, W+84	E69				CC 78		Z+1	R4		
						CC 79		Z+2	R5		AU-4
						CC 95	A-5				
						CC 96	A-4				
						CC 97	A-3				
						CC 98	A-2				
						CC 99	A-1				

Specifications

Main unit

Model	LT-Z32EX6	LT-Z26EX6
Broadcasting systems	B / G / I / D / K / K1 / M (See "Technical information", P. 35)	
Colour systems	PAL, SECAM, NTSC 3.58/4.43MHz	
Channels and frequencies	VHF low channel (VL) = 46.25 to 140.25 MHz VHF high channel (VH) = 147.25 to 423.25 MHz UHF channel (U) = 431.25 to 863.25 MHz · Receives cable channels in mid band (X to Z+2, S1 to S10), super band (S11 to S20) and hyper band (S21 to S41).	
Sound-multiplex systems	NICAM (I / B / G / D / K), A2 (B / G / D / K)	
Teletext systems	FLOF (Fastext), WST (standard system)	
Power requirements	AC 110 V - 240 V, 50/60Hz	
Audio output (Rated power output)	10 W + 10 W	
Speakers	(15 cm x 5.5 cm) oblique x 2	(12 cm x 5 cm) oblique x 2
Power consumption [standby]	120 W [0.5 W]	113 W [0.5 W]
Screen size (visible area size measured diagonally)	81 cm	66 cm
Dimensions (W x H x D: mm) [without stand]	800 x 588.8 x 267.8 [800 x 545 x 137.7]	672 x 518.5 x 244 [672 x 471 x 137.7]
Weights [without stand]	17 kg [15 kg]	14 kg [12 kg]
Accessories	(See "Check accessories", P. 5)	

Terminals / Connectors

Terminal name	Terminal type	Signal type (IN)	Signal type (OUT)	Notes
Input terminals	VIDEO-1	RCA connectors x 6 S-VIDEO connector x 1	Composite video, S-video, Analogue component (576i (625i) / 480i (525i), Progressive : 576p (625p) / 480p (525p), HD : 1080i (1125i), 720p (750p) AUDIO L / R	
	VIDEO-2	RCA connectors x 3 S-VIDEO connector x 1	Composite video, S-video, AUDIO L / R	
	VIDEO-3	RCA connectors x 6	Composite video, Analogue component (576i (625i) / 480i (525i), Progressive : 576p (625p) / 480p (525p), HD : 1080i (1125i), 720p (750p) AUDIO L / R	
	HDMI	HDMI connector x 1	HDMI (576i (625i) / 480i (525i) / 576p (625p) / 480p (525p), 1080i (1125i), 720p (750p))	
	IN HDMI	RCA connectors x 2	AUDIO L / R	
	PC INPUT	D-SUB (15 pins) x 1	Analogue PC signal (P. 36)	
Output terminals	MONITOR OUT	RCA connectors x 3 S-VIDEO connector x 1	Composite video, S-video, Audio L / R	
	Headphone	Stereo mini-jack x 1 (3.5 mm in diameter)	Headphone output	

● We may change the design and specifications without notice.

JVC

JVC

Free Manuals Download Website

<http://myh66.com>

<http://usermanuals.us>

<http://www.somanuals.com>

<http://www.4manuals.cc>

<http://www.manual-lib.com>

<http://www.404manual.com>

<http://www.luxmanual.com>

<http://aubethermostatmanual.com>

Golf course search by state

<http://golfingnear.com>

Email search by domain

<http://emailbydomain.com>

Auto manuals search

<http://auto.somanuals.com>

TV manuals search

<http://tv.somanuals.com>