

2 head Mono VCR



SmartPicture



- **ShowGuard™**
- **Dirty Head Warning**



Let's make things better.



PHILIPS

Download from www.Somanuals.com. All Manuals Search And Download.

2 head Mono VCR



Product Information

Reception

- Tuner: UHF + VHF + Hyperband
- Tuner System: BG, DK, I, K1
- Tuning: FST, 99 presets
- Tuning/Install Features: Auto Channel preset, Manual Search/Store
- Sound System Off Air: Mono

Video System

- Video Systems: REC: PAL/MESECAM
PLAY: PAL/MESECAM/PAL 60
- Picture Improvement System: SMART Picture

Sound System

- Audio Recording System: Linear
- Audio Recording Level: Automatic

User Interface

- OSD Menu Languages: /55: English, Chinese
/75: English
- Tape Position Indicator: yes
- Special Features: Child Lock
- Commercial Skip: yes

Remote Control Unit

- Remote Control type: 1.1
- Remote Control codes: VCR-RC5
- Alternate Channel button: yes

Programming

- Number of Events: 8/year
- Programming Mode: Quick Programming
- Record Speed: Standard Play (SP), Long Play (LP)

Tape Deck

- Number of (S-)VHS Video / FM Audio / Flying Erase Heads: 2/-
- Play: -1, +1, repeat
- Additional Playback Features: Still, Fast Search Speed, Slow Motion
- Repeat Play: 100 times
- Index Related Functions: Next/Previous index search
- Tape Counter: Real Time Counter, Time Left
- Automatic Functions: Auto Play, Auto Rewind, Auto Eject
- Head Cleaning Mode: Automatic
- Dirty Head Warning: yes

Connectors Rear

- Video in/out: RCA/RCA
- Audio in/out: Mono, RCA/RCA
- Terrestrial Antenna In & Out: 75 Ohm

General

- Power Voltage: 110-240V, 50/60Hz
- Backup Presets & Timer Events: ShowGuard (indefinite)
- Backup Clock: 3 minutes
- Power Cons. in Play / Std-By: 12.3/3.6
- Equipment Supplied: Remote Control, Batteries, Aerial Cable
- Weight incl. / excl. package in kg: 4.2/3.2
- Set Size - W x D x H (mm): 360x242x94
- Packaging - W x D x H (mm): 458x357x163

Color

- Front, side panels: Red Silver
- Cover: Red Silver

Product Highlights

• SMART Picture

With this unique feature, you can adapt the picture to your own preference: you can enhance the contours on a cartoon or suppress the noise from a rental tape. We offer you the possibility to play your tapes the way you like to see them.

• ShowGuard™

From now on you never have to programme your timer or channel presets again after you VCR has been disconnected from the power supply for a long time. Due to ShowGuard the timer programmes and channel presets are stored in a memory forever. You can change the timer programmes and channel presets but you can never lose them.

Subject to modification without notice

Let's make things better.



PHILIPS

Free Manuals Download Website

<http://myh66.com>

<http://usermanuals.us>

<http://www.somanuals.com>

<http://www.4manuals.cc>

<http://www.manual-lib.com>

<http://www.404manual.com>

<http://www.luxmanual.com>

<http://aubethermostatmanual.com>

Golf course search by state

<http://golfingnear.com>

Email search by domain

<http://emailbydomain.com>

Auto manuals search

<http://auto.somanuals.com>

TV manuals search

<http://tv.somanuals.com>