


## 6 head HiFi VCR



# MYVCR

- Turbo Drive with Tape Position Indicator
- Digital Studio Picture Control
- Plug & Play
- Turbo Timer with Net Name Detection
- Record Link
- Audio Stereo Cinch Outputs

Silver Shadow + White



Let's make things better.



PHILIPS

# 6 head HiFi VCR



## Product information

### Reception - Installation

- Tuner: Hyperband, UHF, VHF
- Tuning - presets: PLL, CH entry, 99 presets
- Time/Date Download: PDC (Time/Date), Text (Time)

### User Interface

- Record Speed: Long Play, Standard Play
- Record Speed Selection: Auto LP, Per Menu
- Picture Improvement System: Digital Studio Picture Control
- Audio Recording Level: Automatic
- Special Features: Auto Standby On/Off, Child Lock, Display On/Off
- TV Related Functions: 16:9 (pin 8)

### On Tape Standard

- Additional Playback Standard: BLACK & WHITE, NTSC Playback on PAL TV

### Remote Control Unit

- Remote Control - Type Number: RT121/111
- Remote Control - Codes: VCR1, TV Commands

### Connectors Rear

- EXT1: Black, Euro CVBS in/out
- EXT2: Black, Euro Decoder, RGB loop through
- Rear Audio Connector: Cinch Stereo Out
- Terrestrial Antenna In/Out: 75 Ohms (IECtype)
- Mains Connector: Standard (IECtype)

### Tape Deck

- Number of Video / FM Audio / Flying Erase Heads: 4 / 2 / 0
- Play: +1, -1, Repeat
- Additional Playback Features: Perfect Still, Multiple Search Speed, Multiple Slow Motion Speed
- Index Related Functions: Blank Tape Search, Next/Prev. index search
- Head Cleaning Mode: Automatic
- Tape Length Recognition: Automatic
- Tape Counter: Linear Relative (h.m.s), Time Left (h.m.), Tape Position Indicator
- Winding / Rewinding Time (E180): 100 sec.
- Automatic Functions at Tape End: Rewind after Play, Eject after Record

### Programming

- Number of Events: 6/month
- Record Control & Transmitter Identification: Net-name detection PDC, VPS
- Special Timer Programming: Turbo Timer
- Record Link: SCART 2

### General

- Voltage: 198-264 V
- Frequency: 50Hz
- Backup Presets: 1yr
- Backup Clock - Calendar - Timer Event: 3hrs
- Power Consumption Play / Std-By / Low Power Std-By in W: 16 / 4.4 / <4
- Set Size - W x D x H in mm: 380 x 260 x 93
- Packaging - W x D x H in mm: 450 x 382 x 180
- Weight Including / Excluding package in kg: 5.5 / 3.6
- Equipment Supplied: Antenna, Mains cord, Batteries

## Product Highlights

### • Digital Studio Picture Control

Digital Studio Picture Control keeps checking the quality of your videotapes and reproduces the best possible picture performance. Philips' Digital Studio Picture Control optimises the playback quality. It measures the characteristics of the tape, adapts the resolution and reduces the picture noise.

### • Turbo Timer with Net Name Detection

Is Timer Programming complicated? No!  
Is Timer Programming time consuming? No!  
Just press the Turbo Timer button on the remote control, select the TV channel you want to record (directly by its name), set the start and the end time. That's it. All it takes is only a few seconds.

### • Record Link

Your satellite receiver is equipped with a Timer function? Connect both your VCR and the satellite receiver with a SCART cable and make use of the „Record Link“ function. You just have to activate it and switch your VCR to std-by. As soon as the satellite receiver gets active, the VCR switches on and is set in the record mode. At the end of the recording it returns automatically to Stand-by.

### • Turbo Drive

Enjoy the ease of use and the comfort of one of the fastest VCR decks in the world.

### • Plug & Play

With Plug & Play, the VCR welcomes you and leads you through the installation steps. You just have to set your language and the country you live in. The VCR does the rest.

	VR670W/58	VR670W/39	VR670W/16	VR670W/07	VR670W/02
Tuning/Install Features	Auto Search, Manual Store, Plug & Play, Welcome Screen	Auto Tuning, Manual Store, Plug & Play, Welcome Screen	Auto Tuning, Manual Store, Plug & Play, Welcome Screen	Auto Install, Manual Store, Plug & Play, Welcome Screen	Auto Tuning, Manual Store, Plug & Play, Welcome Screen
TV Systems Off Air	PAL B/G PAL D/K SECAM B/G SECAM D/K	PAL B/G PAL I SECAM B/G SECAM L/L'	PAL B/G	PAL I	PAL B/G
Sound Systems	German Stereo, Mono, NICAM	German Stereo, Mono, NICAM Splitter	German Stereo, Mono, NICAM, Pal G	German Stereo, Mono, NICAM, Pal I	German Stereo, Mono, Pal G
Modulator	Pal GK (switchable)	—	Electr. On/Off switch, Manual Frequency Adjustment	Auto Seek, Electr. On/Off switch, Manual Frequency Adjustment	Electr. On/Off switch, Manual Frequency Adjustment
Frequency Adj. Range	Ch 21 - Ch 55	—	Ch 21 - Ch 55	Ch 21 - Ch 55	Ch 21 - Ch 55
Preadj. modulation frequency	591.25 MHz (Ch 36)	—	591.25 MHz (Ch 36)	583.25 MHz (Ch 35)	591.25 MHz (Ch 36)
OSD Menu Languages	Czech, Danish, Dutch, English, Finnish, French, German, Hungarian, Italian, Norwegian, Polish, Portuguese, Russian Cyrillic, Slovak, Spanish, Swedish	Czech, Danish, Dutch, English, Finnish, French, German, Hungarian, Italian, Norwegian, Polish, Portuguese, Russian Cyrillic, Slovak, Spanish, Swedish	Czech, Danish, Dutch, English, Finnish, French, German, Hungarian, Italian, Norwegian, Polish, Portuguese, Russian Cyrillic, Slovak, Spanish, Swedish	English	Czech, Danish, Dutch, English, Finnish, French, German, Hungarian, Italian, Norwegian, Polish, Portuguese, Russian Cyrillic, Slovak, Spanish, Swedish
Record / Playback Standard	MESECAM, PAL	MESECAM, PAL, SECAM	PAL	PAL	PAL
Programming System	Showview Daily/Weekly, Programming by Net-Name	Showview Daily/Weekly, Programming by Net-Name	Showview Daily/Weekly, Programming by Net-Name	Video Plus +, Daily/Weekly, Programming by Net-Name	Showview Daily/Weekly, Programming by Net-Name

Subject to modification without notice

Show View and Video+ are registered Trademarks of Gemstar Development Cooperation.

Let's make things better.



PHILIPS

## Free Manuals Download Website

<http://myh66.com>

<http://usermanuals.us>

<http://www.somanuals.com>

<http://www.4manuals.cc>

<http://www.manual-lib.com>

<http://www.404manual.com>

<http://www.luxmanual.com>

<http://aubethermostatmanual.com>

Golf course search by state

<http://golfingnear.com>

Email search by domain

<http://emailbydomain.com>

Auto manuals search

<http://auto.somanuals.com>

TV manuals search

<http://tv.somanuals.com>