

2 Head Mono VCR

VR101

Football Edition

- **Digital Studio Picture Control** - obtain the best possible picture quality regardless of the tape you use.
- **Laser-Cut Video Heads** have a better profile for a superior head/tape contact. Lesser wear guarantees longer life and higher performance quality.
- **Plug & Play** - the VCR welcomes you and leads you through the installation steps. You just have to set your language and the country you live in. The VCR does the rest.
- **Follow TV** sorts the channels in the same order as already found in the TV.
- **Direct Record** - just insert a cassette, push the record button and the programme you see on TV gets recorded.
- **Automatic Satellite Recording**
- **NTSC Playback**

SHOWVIEW

DIGITAL
STUDIO
PICTURE
CONTROL

FOLLOW...
...TV

NTSC
PLAYBACK



Let's make things better.



PHILIPS

Download from www.somanuals.com. All Manuals Search And Download.

Product information

Reception

- Tuner: Full Tuner (UHF + VHF + Hyperband)
- Tuning: PLL, CH entry, 99 presets
- Tuning/Install Features: Auto Tuning, Manual Store, Plug & Play, welcome screen
- Time/Date Download: PDC (Time/Date), Text (Time)
- Sound Systems: Mono

User Interface

- OSD Menu Languages: Czech, Danish, Dutch, English, Finnish, French, German, Hungarian, Italian, Norwegian, Polish, Portugese, Russian Cyrillic, Slovak, Spanish, Swedish
- Special Features: Auto Standby On/Off, Child Lock, Display On/Off
- Picture Improvement System: Digital Studio Picture Control
- TV Related Functions: Direct Record, Follow TV

Remote Control Unit

- Remote Control - code: TV-RC5, VCR1-RC5

Connectors Rear

- EXT1: Black, Euro CVBS in/out
- EXT2: Black, Euro Decoder, RGB loop through
- Terrestrial Antenna In / Out: 75 Ohms (IECtype)
- Mains Connector: Standard (IECtype)

Tape Deck

- Number of Video / FM Audio / Flying Erase Heads: 2 / 0 / 0
- Play: +1, -1, Repeat
- Playback Features: Standard Still, Multiple Search Speed
- Index Search Related Functions: Blank Tape Search, Next/Prev. index search
- Head Cleaning Mode: Automatic
- Tape Counter: Linear Relative (h.m.s)
- Wind / Rewind Time (E180): 260sec. / 170 sec.
- Automatic Functions at Tape End: Rewind after Play - Eject after Record

Programming

- Number of Events: 6/month
- Programming Mode: OTR, Remote
- Record Control & Transmitter Identification: PDC, VPS
- Programming System: Daily/Weekly, Showview
- Automatic SAT. Recording: SCART 2
- Record Speed: Standard Play

On Tape Standard

- Additional Playback Standard: NTSC Playback on PAL TV

General

- Voltage / Frequency: 198-264 V / 50Hz
- Backup Presets: 1yr
- Backup Clock, Calendar, Timer: 3 hrs
- Power Cons. in Play / Std-By / Low Power Std By: 12.5 / 4.4 / < 4W
- Weight incl. / excl. package in kg: 5.5 / 3.6
- Set Size - W x D x H (mm): 380 x 260 x 93
- Packaging - W x D x H (mm): 450 x 382 x 180
- Equipment Supplied: Aerial, Mains cord, Batteries

Product Highlights

• Digital Studio Picture Control

Digital Studio Picture Control keeps checking the quality of your videotapes and reproduces the best possible picture performance. Philips' Digital Studio Picture Control optimises the playback quality. It measures the characteristics of the tape, adapts the resolution and reduces the picture noise.

• Automatic Satellite Recording

You want to record a programme from your satellite receiver or any other external device when you're not at home, or while you watch another programme at the same time? And you want to set your receiver to come on at a specific time?

Just activate the "RECORD PREPARED MODE", put the set in standby and programme the desired timer on your satellite receiver – and upon activation of the satellite receiver, the set will start the recording simultaneously.



	VR101/02	VR101/39	VR101/58
TV Systems Off Air	PAL B/G	PAL B/G, PAL I, SECAM B/G, SECAM L/L1	PAL B/G, PAL D/K, SECAM B/G, SECAM D/K
Modulator	Pal G	Splitter	Pal GK (switchable)
Modulator Features	Electr. On/Off switch, Manual Frequency Adjustment	–	Electr. On/Off switch, Manual Frequency Adjustment
Frequency Adj. Range	Ch 21 - Ch 55	–	Ch 21 - Ch 55
Preadj. modulation frequency	591.25 MHz (Ch 36)	–	591.25 MHz (Ch 36)
Remote Control - type	RT111/101	RT111/104	RT111/101
Record / Playback Standard	PAL	MESECAM, PAL, SECAM	MESECAM, PAL

Subject to modification without notice

Show View is a registered Trademark of Gemstar Development Cooperation.

Let's make things better.



PHILIPS

Free Manuals Download Website

<http://myh66.com>

<http://usermanuals.us>

<http://www.somanuals.com>

<http://www.4manuals.cc>

<http://www.manual-lib.com>

<http://www.404manual.com>

<http://www.luxmanual.com>

<http://aubethermostatmanual.com>

Golf course search by state

<http://golfingnear.com>

Email search by domain

<http://emailbydomain.com>

Auto manuals search

<http://auto.somanuals.com>

TV manuals search

<http://tv.somanuals.com>