

## Specifications



<b>Generator</b>	Generator Model	QB1300	QB2800	QB3300	QB5500E	QB7700E
	Frequency(Hz)	60Hz	60Hz	60Hz	60Hz	60Hz
	Rated AC voltage (volts)	120	120	120	120/240	120/240
	AC Circuit breaker	10A(1pcs)	22A (1pcs)	27A (1pcs)	22A(2 pcs)	
	Rated AC Output (watts)	1100	2500	3000	5000	7200
	Peak AC (watts)	1300	2800	3300	5500	7700
	DC Output (volts)	12v	12v	12v	12v	12v
<b>Engine</b>	Engine Model	WG90	WG160	WG200	WG340	WG405
	Engine(HP)	2.6	5.5	6.7	11.0	14.0
	Low level oil alert	No	With	With	With	With
	Gas tank capacity	1.3 Gallon	3 Gallon	3 Gallon	6 Gallon	6 Gallon
	Starting system	Recoil	Recoil	Recoil	Recoil&Electric	Recoil&Electric
	Noise level db(A)@7m	65-68	70-72	72-74	68-74	68-74
<b>Standard Features</b>	Gas level gauge	Std	Std	Std	Std	Std
	Voltmeter	Std	Std	Std	Std	Std
	AC receptacles	15A AC120V 1pc	20A AC120v 2PCS	20A AC120v 2PCS	20A AC120V 4PCS	20A AC120V 4PCS
	AC twist lock receptacle	N/A	N/A	N/A	30A AC240V 1PC	30A AC240V 1PC
	Two wheel kit&tow handle	N/A	N/A	Std	Std	Std
<b>General Information</b>	Dimensions L*W*H	18"x14"x15.5"	22"x17.5"x19.5"	22"x17.5"x19.5"	25"x21"x25"	25"x21"x25"
	Gross weight	65 lbs	108 lbs	117 lbs	187 lbs	209 lbs

## Free Manuals Download Website

<http://myh66.com>

<http://usermanuals.us>

<http://www.somanuals.com>

<http://www.4manuals.cc>

<http://www.manual-lib.com>

<http://www.404manual.com>

<http://www.luxmanual.com>

<http://aubethermostatmanual.com>

Golf course search by state

<http://golfingnear.com>

Email search by domain

<http://emailbydomain.com>

Auto manuals search

<http://auto.somanuals.com>

TV manuals search

<http://tv.somanuals.com>