

Home Wireless Alarm System

Easy to install security protection for your property



Deterrence is the best defense

By positioning the Anti-Intrusion Siren & 8 Window Stickers in visible locations you send a strong message to potential burglars & greatly decrease your chances of being broken into.

Bad news for intruders

If you are broken into you have protection from a window / doorway sensor & 2 PIR area motion sensors to trigger an audible anti-intrusion siren, loud enough to register 110 decibels.

Easy to install & operate

The Touchpad Alarm Control Unit plugs into your power point and easily connects to the siren via cable (included) The sensors & remote controls connect wirelessly and are battery powered (batteries included in the pack)

No false alarms, no hassles

The PIR sensor & door alarm can be armed after a 30 second delay & will not be triggered unless there is an object of significant size detected.

Complete peace of mind at an affordable price

Have the satisfaction of protecting your property, safeguarding your loved ones & deterring thieves with no ongoing monitoring fees. Perfect for homes, apartments & small businesses.

Intelligent Security Protection

- 2x** Alarm PIR Motion Sensors
- 1x** Window / Doorway Sensor
- 1x** Loud Anti-Intrusion Siren
- 1x** Touchpad Alarm Control Unit
- 2x** Keypad Remote Controls
- 8x** Window Deterrent Stickers

Home Wireless Alarm System

Easy to install security protection for your property



Specifications

Wireless Control Panel

Power voltage	DC 9V
Wireless transmission frequency	433MHz± 0.5MHz
Alarm siren decibel	≥ 110db
Working temperature	-10°C ~ +40°C
Relative humidity	≤ 90%
Maximum Paired Devices	Up to 28

Door Sensor

Power voltage	DC 8.4V ~ 12V (includes A23DC 12V battery)
Wireless transmission frequency	433MHz± 0.2MHz
Transmission distance	Up to 262ft / 80m (line of sight); 65ft / 20m (typical)
Working temperature	14°F ~ 104°F / -10°C ~ +40°C
Relative humidity	≤ 90%

PIR Motion Sensor

Power voltage	DC 7.2V ~ 9V (includes 6F22 9V battery)
Wireless transmission frequency	433MHz± 0.2MHz
Transmission distance	Up to 262ft / 80m (line of sight) 65ft / 20m (typical)
Warm-up time	≤ 150s
Transmission interval	≤ 35s
Detectible speed	0.3 ~ 3m/s
Detectible distance	16 ~ 50ft / 5 ~ 15m
Detectible angle	110°
Interference of small animals	F1.18" x 2" / F30 x 50mm
Interference of white light	≥ 2000L
Working temperature	14°F ~ 104°F / -10°C ~ +40°C
Relative humidity	≤ 90%

Remote Controls

Power voltage	DC 8.4V ~ 12V (includes A27DC 12V battery)
Standby ampere	= 0A
Alarm ampere	15mA
Wireless transmission frequency	433MHz± 0.2MHz
Transmission distance	Up to 262ft / 80m (line of sight); 65ft / 20m (typical)
Working temperature	14°F ~ 104°F / -10°C ~ +40°C
Relative humidity	≤ 90%

Package Contents

- Touchpad Alarm Control Unit
- Alarm PIR Motion Sensors x 2
- Keypad Remote Control Units x 2
- Window / Door Protection Sensor
- Audible Anti-Intrusion Alarm
- Theft Deterrent Stickers x 8
- Operating Instructions

Free Manuals Download Website

<http://myh66.com>

<http://usermanuals.us>

<http://www.somanuals.com>

<http://www.4manuals.cc>

<http://www.manual-lib.com>

<http://www.404manual.com>

<http://www.luxmanual.com>

<http://aubethermostatmanual.com>

Golf course search by state

<http://golfingnear.com>

Email search by domain

<http://emailbydomain.com>

Auto manuals search

<http://auto.somanuals.com>

TV manuals search

<http://tv.somanuals.com>