

# BM-21

SONY

## Pressman® Standard Cassette Dictator

---

- ▲ **SLIDE SWITCH CONTROL**
- ▲ **METAL CASE**
- **LCD TAPE COUNTER**
- **VOICE OPERATED RECORDING (VOR) WITH IC SENSITIVITY ADJUSTMENT**
- **BATTERY LED/VOICE MIRROR**
- **SAFETY LOCK**
- ▲ **END OF TAPE ALARM/AUTOMATIC MOTOR SHUT-OFF**
- **CUE AND REVIEW**
- **MICROPHONE JACK**
- **AC COMPATIBILITY**
- **EARPHONE JACK**
- **HINGED BATTERY LID**
  
- ▲ **STEP-UP FEATURE**    ▶ **NEW FEATURE**



PRESSMAN

## features

- **STANDARD CASSETTE SYSTEM** uses readily available cassettes for recording and playback convenience using a variety of tape lengths
- ▲ **SLIDE SWITCH CONTROL** provides instant Dictation/Stop/Rewind/Listen operation with just one finger
- ▲ **METAL CASE** is designed to withstand rugged use while dictating in or out of office, in the car and elsewhere
- **LCD TAPE COUNTER** uses a bright Liquid Crystal Display to give you a numerical indication of tape length, for rapid access when editing and listening
- **VOICE OPERATED RECORDING (VOR) WITH MIC SENSITIVITY ADJUSTMENT** permits activation of the recorder only when VOR senses audible sound, to conserve tape and eliminate soundless pauses during playback
- **BATTERY LED/VOICE MIRROR** confirms recording by mirroring voice with LED illumination, and also provides indication of relative battery strength
- **SAFETY LOCK** prevents accidental operation while carrying the unit
- ▲ **END OF TAPE ALARM/AUTOMATIC MOTOR SHUT-OFF** alerts you that the end of the tape has been reached and helps to reduce mechanical wear and conserve batteries
- **CUE AND REVIEW** provides sound during Fast Forward or Rewind to help find specific passages
- **MICROPHONE JACK** allows you to connect an optional microphone
- **AC COMPATIBILITY** permits two-way operation, on available replaceable batteries or optional AC power adaptor
- **EARPHONE JACK** for individual listening to the playback and for privacy without disturbing others, using optional earphone
- **HINGED BATTERY LID** prevents accidental loss

## specifications

- TAPE SYSTEM:** 4 track, 2 channel monaural cassette  
**FREQUENCY RESPONSE:** 200 - 8000Hz  
**MICROPHONE:** Built-in electret condenser  
**INPUTS:** DC In, 3V; External Microphone  
**OUTPUTS:** Earphone mini jack  
**SPEAKER:** Mono x 1, 1 7/16" (36mm) dia  
**POWER OUTPUT:** 240mw (at 10% THD)  
**POWER REQUIREMENTS:** DC 3V with "AA" x 2 batteries  
 AC 120V 60Hz  
**BATTERY LIFE:** Approx 3 hrs with standard Batteries  
 Approx 12 hrs with Sony alkaline batteries  
**DIMENSIONS (WHD):** 3 1/2" x 5" x 1 1/4" (88.1 x 129.2 x 32.3mm)  
**WEIGHT:** 10 1/2 oz (300g) with batteries  
**OPTIONAL ACCESSORIES:** AC-E30L AC Adaptor

©2002 Sony Electronics Inc.  
 Reproduction in whole or in part without written permission is prohibited. All rights reserved. Sony and Pressman are trademarks of Sony.  
 Features and specifications are subject to change without notice. Non-metric weights and measures are approximate.

## Free Manuals Download Website

<http://myh66.com>

<http://usermanuals.us>

<http://www.somanuals.com>

<http://www.4manuals.cc>

<http://www.manual-lib.com>

<http://www.404manual.com>

<http://www.luxmanual.com>

<http://aubethermostatmanual.com>

Golf course search by state

<http://golfingnear.com>

Email search by domain

<http://emailbydomain.com>

Auto manuals search

<http://auto.somanuals.com>

TV manuals search

<http://tv.somanuals.com>