

# PMM-60A and PMM-120A

60 or 120 Watt Professional Grade  
Public Address Mixer / Amplifier



PMM-120A Shown

## Specifications

PMM-60A • 60 WATTS RMS POWER

PMM-120A • 120 WATTS RMS POWER

### Both Include:

- 6 Mic Inputs (4 XLR Connectors)
- 70/25 Volt or 4, 8, 16 Ohm Output
- Priority Paging with Auto Mute Function
- Music on Hold Line Level Out w/ Level Control
- 600 Ohm Telephone Paging Input
- Master Volume Control
- Separate Bass & Treble Control on Output Stage
- 2 Auto Summing Stereo to Mono Aux Inputs
- Accessory AC Outlet

Specifications subject to change.



## Free Manuals Download Website

<http://myh66.com>

<http://usermanuals.us>

<http://www.somanuals.com>

<http://www.4manuals.cc>

<http://www.manual-lib.com>

<http://www.404manual.com>

<http://www.luxmanual.com>

<http://aubethermostatmanual.com>

Golf course search by state

<http://golfingnear.com>

Email search by domain

<http://emailbydomain.com>

Auto manuals search

<http://auto.somanuals.com>

TV manuals search

<http://tv.somanuals.com>