



Web Ready 8CH DVR System

w/ 8 Outdoor Night Vision CCD Color Cameras and 8" LCD Monitor

COMPLETE SYSTEM



1 YEAR WARRANTY
Manufacturer Defects

BONUS

Window
Warning
Stickers

SVAT WARNING SECURITY SYSTEM x8

CF Card Backup Feature

EASY setup



WWW

Access your DVR
from anywhere
in the world



Wired

250GB HDD
Records up to 1½ Years

**8" Ultra Slim
LCD Monitor**

**8 Hi-Res
CCD Cameras**

**Model #:
CLEARVU3**
www.svat.com

Web Ready 8CH DVR System w/ 8 Outdoor Night Vision CCD Color Cameras and 8" LCD Monitor



NOTE: Product May Appear Different Than Shown

LCD MONITOR

1. LCD Screen
2. Power Button
3. AV2 In Port
4. AV1 In Port
5. 3.5mm Headphone Jack
6. DC Power Input (12V)
7. Speakers
8. Mounting Rails
9. Mounting Hole
10. AV1/AV2 Buttons
11. Pics Button
12. Auto Button

13. Volume Increase Button
14. Volume Decrease Button
15. Up Arrow Button
16. Down Arrow Button
17. Menu Button
18. Mute Button

CCD CAMERAS

19. Sun Shield
20. Infrared (IR) LEDs
21. CDS Sensor
22. Camera Housing
23. Camera Mount
24. Connection to Audio/Video Wire

8 CHANNEL DVR RECORDER

25. LED Indicator - Power,HDD Activity
26. Removable/Lockable HDD Casing
27. Camera Channel Select (1-8)
28. Record Button
29. Stop Button
30. Play Button
31. Pause Button
32. Split Button
33. Auto Sequencing Button
34. Search Button
35. Menu Button
36. Exit/Info Button
37. Enter/Display Button
38. CF Card Slot
39. Left Button
40. Right Button
41. Up Button
42. Down Button
43. LED Indicators
44. BNC Video Inputs
45. DC Power Input (12V).
46. Alarm Input/Output Port
47. Audio Inputs
48. RCA Audio Output
49. BNC Video Output

50. Ethernet Port
51. BNC SPOT Video Output
52. Cooling Fan

CV67 Cameras Do Not Support Audio



60ft Extension Wire
Ends on the 60ft extension wire. Power (red), & Video (yellow)

RCA to BNC Connector
Connects RCA cameras to the video input on the back of the DVR

WHERE DO I USE THIS?

At **home** to watch your:

- Garage
- Backyard
- Property
- Driveway

At **work** to watch your:

- Entrance Ways
- Employees
- Parking Lot
- Warehouse



WHAT IS INCLUDED WITH THIS SYSTEM?



- 10 RCA to BNC Connectors
- 10ft RJ-45 Ethernet Cable
- 1 RCA Female to 3.5mm (male) A/V Wire
- 1 Power Adapter for LCD Monitor
- 1 10ft RCA to RCA (male) A/V Wire
- 1 Power Adapter for DVR
- 1 Year Warranty
- Quick Start Guide
- Instruction Manual
- 4 Window Warning Stickers
- Online/Toll Free Support

UPC

CLEARVU3 ~ 871363006578

QUALITY	2500GB 8CH DVR RECORDING CHART						
FRAME RATE PER SEC	0.5	1	2	4	7.5	15	30
Low (days)	580	300	150	75	40	20	10
Med (days)	500	250	130	65	35	15	8
High (days)	300	150	75	35	20	10	5

SPECIFICATIONS (for more detailed specifications visit www.svat.com)

INDOOR DVR

- FunctionalitySimplex
- Video CompressionMJPEG
- Live ResolutionNTSC / 704 X 480 / PAL: 704 X 576
- Recording Frame Rate30FPS
- Recording Time580 Days (0.5 Frames Per Second)
- Recording QualitiesLow/Medium/High
- Storage CapacityMax 500GB (HDD), 250GB included
- Video FormatNTSC/PAL
- Live DisplaySingle / Quad / 9-Split
- Network LAN IPDynamic, Static



- Network Connection10/100 BaseT Ethernet (RJ-45)
 - Back-upCF Card, Max 4GB
 - Play Search ModeTime/Date/Event List
 - OSD Language DisplayMulti-Language
 - Time and Date Stamp DisplayYes
 - Password ProtectionYes, Menu Password
 - Operating SystemProprietary
 - Automatic Overwrite OptionYes
 - Power Input12V/4.2A
- LCD MONITOR**
- Display8" Color LCD
 - Resolution480 x 468
 - Video Inputs2x 3.5mm jack (RCA to 3.5mm wire included)
 - Audio Input2x 3.5mm jack (RCA to 3.5mm wire included)
 - Audio Output1x 3.5mm headphone jack
 - LCD Profile Ratio4.3
 - Response Time(ms)Tr:10ms/Tf:20ms
 - LanguagesEnglish, Russian, German, Italian, Chinese Dutch, Japanese, Spanish, Portuguese, French
 - Speaker Wattage0.3W x 2
 - Power InputDC 12V 1200mA
- OUTDOOR CAMERA (CV67)**
- Camera TypeBullet
 - Image Sensor1/4" Color Sharp CCD
 - Resolution420 TV Lines
 - IP RatingIP65
 - Focal Length3.6mm
 - Focus TypeFixed
 - Night VisionYes
 - Number of IR LEDs and Range12, up to 15ft
 - IR LED ControlAutomatic (CDS Sensor)
 - Min. Illumination0 lux
 - Video Output60ft 4 PIN DIN to RCA Video/Power Wire
 - TV SystemNTSC
 - Viewing Angle60 Degrees
 - Housing MaterialAnodized Aluminum
 - Operating Temperature-14°F ~ 122°F
 - Camera Power InputDC 12V 300mA

- DIMENSIONS**
- Monitor: 8.5" x 8.125" x 5.125" ~ 1.6lbs
 - DVR: 16.94" x 11.63" x 2.63" ~ 8.75lbs
 - Camera: 5.5"x5" x 4.22" ~ 0.85lbs

SVAT Electronics
Toll Free: 1.866.946.7828
now you can see



Download from Www.Somanuals.com. All Manuals Search And Download.

SVAT, CLEARVU and "now you can see" are trademarks of SVAT Electronics.
©2007 SVAT Electronics
All Rights Reserved



Model #:
CLEARVU3
www.svat.com

Free Manuals Download Website

<http://myh66.com>

<http://usermanuals.us>

<http://www.somanuals.com>

<http://www.4manuals.cc>

<http://www.manual-lib.com>

<http://www.404manual.com>

<http://www.luxmanual.com>

<http://aubethermostatmanual.com>

Golf course search by state

<http://golfingnear.com>

Email search by domain

<http://emailbydomain.com>

Auto manuals search

<http://auto.somanuals.com>

TV manuals search

<http://tv.somanuals.com>