

## **Acer Projector PD113P Summary (v2-2-1)**

### **PD113P**

*Chic, compelling and compact*

The Acer PD113P is a stylish, powerful, conveniently mobile, and neat projector ideally suited for use in meeting venues, or as a home projector. Its 200 W bulb delivers a class-leading brightness of 1,700 ANSI Lumens for effortless viewing — even in bright environments. What's more, economy mode promises a quieter environment, lower power consumption, and longer lamp life.

#### **Easy to take with you**

- Weighing in at a little over 2 kg, the Acer PD113P projects crisply focused images with a contrast ratio of 2,000:1 and superb 1,700 ANSI Lumens brightness.
- A compact form-factor makes the Acer PD113P easy to transport between venues.

#### **Runs quietly**

- Running quietly, the Acer PD113P lets the audience listen to a presentation or watch a movie without distraction.
- Economy mode uses less power, reduces noise, and assures a longer lamp life.

#### **Generous functionality**

- The Acer PD113P provides full-feature performance at a budget-friendly cost.
- Features SVGA resolution that permits high-definition video in the living room, or vibrant boardroom presentations.
- Fully compatible with the latest digital equipment and sophisticated notebooks, this projector can be installed for either floor-mounted or ceiling-mounted applications.
- The Empowering key on the remote control allows you to easily select display modes.

#### **Multimedia wonder**

- Comprehensive input-signal support includes VGA, NTSC, PAL, SECAM and HDTV. Progressive scan (P-scan) capability provides film-like video quality.
- A wide range of multimedia formats are supported, including composite, S-video, and D-sub — ensuring easy connection to a PC, notebook, DVD or game console.
- Three versatile display modes (PC, Movie and User-defined) automatically select the best settings for ultimate picture clarity.
- The Acer PD113P offers flexible 4:3 and 16:9 aspect ratio selections.

#### **Have your say**

- Select your own projector startup image — a company logo or personalized picture — when using the Acer PD113P.
- User information may be indicated on the startup screen as well.

<b>A: Screen size (diagonal)</b>	<b>Screen size (W x H)</b>	<b>B: Distance (from screen)</b>
27.5"	0.56 x 0.42 m	1.2 m
60"	1.2 x 0.9 m	2.2 - 2.6 m
80"	1.6 x 1.2 m	2.9 - 3.5 m
100"	2.0 x 1.5 m	3.6 - 4.4 m
200"	4.1 x 3.0 m	7.3 - 8.7 m
330"	6.7 x 5.0 m	12 m

zoom ratio : 1.2x

<b>Acer Projector PD113P Quick Spec</b>	
<b>Projection system</b>	DLP™
<b>Resolution</b>	Native SVGA (800 x 600) Maximum SXGA (1,280 x 1,024)
<b>Brightness</b>	1,700 ANSI Lumens (standard); 1,300 ANSI Lumens (economy)
<b>Computer compatibility</b>	IBM PC and compatibles, Apple Macintosh, iMac and VESA standards: SXGA, XGA, VGA (resizing)
<b>Video compatibility</b>	NTSC (3.58/4.43), PAL (B/D/G/H/I/M/N), SECAM (B/D/G/K/K1/L), HDTV (720p, 1080i), EDTV (480p, 576p), SDTV (480i, 576i)
<b>Aspect ratio</b>	4:3 (native), 16:9
<b>Contrast ratio</b>	2000:1
<b>Displayable colors</b>	16.7 million colors
<b>Noise level</b>	31 dBA (standard mode); 29 dBA (economy mode)
<b>Projection lens</b>	F/2.5 to 2.7, f = 20.2 to 24.2 mm 1:1.2 manual zoom and manual focus
<b>Projection screen size (diagonal)</b>	0.7 m (27.5") to 8.4 m (330")
<b>Projection distance</b>	1.2 m (3.94') to 12 m (39.4')
<b>Throw ratio</b>	55" @ 2 m
<b>Horizontal scan rate</b>	31 to 79 kHz

<b>Acer Projector PD113P Quick Spec</b>	
<b>Vertical refresh scan rate</b>	50 to 85 Hz
<b>Lamp type</b>	200 W user replaceable NSH lamp
<b>Lamp life</b>	2,000 hours (standard); 3,000 hours (economy)
<b>Keystone correction</b>	+/-15 degrees
<b>Audio</b>	One internal speaker with 2 W output
<b>Weight</b>	2.3 kg (5.1 lbs.)
<b>Dimensions</b>	256 x 198 x 92 mm (10.1 x 7.8 x 3.6 inches)
<b>Remote control</b>	Laser pointer* and PgUp/PgDn function
<b>Power supply</b>	AC 100 to 240 V auto-switching power supply
<b>Power consumption</b>	250 W
<b>Operating temperature</b>	5 °C to 35 °C (41 °F to 95 °F)
<b>Uniformity</b>	90%
<b>I/O connectors</b>	<p>Computer input:</p> <ul style="list-style-type: none"> <li>• HDB 15-pin D-sub (VGA/component/HDTV)</li> <li>• 3.5 mm audio mini jack</li> </ul> <p>AV input:</p> <ul style="list-style-type: none"> <li>• HDB 15-pin D-sub (VGA/component/HDTV, same as above)</li> <li>• Composite video RCA jack</li> <li>• S-video mini DIN</li> <li>• 3.5 mm audio mini jack (same as above)</li> </ul> <p>Output:</p> <ul style="list-style-type: none"> <li>• USB connector for remote computer control</li> </ul>
<b>Standard package contents</b>	<p>AC power cord  VGA cable (15-pin D-sub)  Composite video cable (RCA)  S-video cable  VGA (D-sub) to component/HDTV cable  USB cable  Audio cable (mini to mini phone jack)  Remote control with laser pointer* and PgUp/PgDn function  Two batteries (for remote control)  User's Guide (CD-ROM)  Quick start card  Lens cap  Carrying case</p>

\*Note: Laser Pointer is not available on models sold in Japan.

## Free Manuals Download Website

<http://myh66.com>

<http://usermanuals.us>

<http://www.somanuals.com>

<http://www.4manuals.cc>

<http://www.manual-lib.com>

<http://www.404manual.com>

<http://www.luxmanual.com>

<http://aubethermostatmanual.com>

Golf course search by state

<http://golfingnear.com>

Email search by domain

<http://emailbydomain.com>

Auto manuals search

<http://auto.somanuals.com>

TV manuals search

<http://tv.somanuals.com>